

LUX FLAM 1600



Poate fi utilizata cu Big – Medium si Micro Torch

Descriere	Unitate de masura	LUX FLAM 1600
Tensiune	Volt.	220/230
Frecventa	Hz.	50
Putere	Watt.	950
Presiune	Bar.	1,1
Productie gaz	Lt/ora	160
Consum de apa	Cc/ora	80
Consum de "Blu flam"	Cc/ora	30
Capacitate rezervor Blu flam	cc	280
Greutate	Kg.	45
Solutie electrolitic	Lt.	3

LUX FLAM 800



Poate fi utilizata cu Medium and Micro Torch

Descriere	Unitate de masura	LUX FLAM 800
Tensiune	Volt.	220/230
Frecventa	Hz.	50
Putere	Watt.	590
Presiune	Bar.	1,1
Productie gaz	Lt/ora	80
Consum de apa	Cc/ora	41
Consum "Blu flam"	Cc/ora	15
Capacitate rezervor Blu flam	cc	225
Greutate	Kg.	25
Solutie electrolitic	Lt.	1

LUX FLAM 450



Poate fi utilizata cu Micro Torch

Descriere	Unitate de masura	LUX FLAM 450
Tensiune	Volt.	220/230
Frecventa	Hz.	50
Putere	Watt.	280
Presiune	Bar.	1,1
Productie gaz	Lt/hr	45
Consum de apa	Cc/hr	22
Consum "Blu flam"	Cc/hr	9
Capacitate rezervor Blu flam	cc	150
Greutate	Kg.	14
Solutie electrolitic	Lt.	0,5



ECHIPAMENTE - TEHNOLOGIE - SERVICE SRL

Sediu: Baia Mare, str.Granicerilor nr.79, tel.0262-259.205, fax.0262-279.544

Birou comercial: Bucuresti, str.Siriului nr.60A, sector 1, tel.021-232.25.48, fax.021-232.06.29

Cod unic: R16282595, Nr.inregistrare: J24/492/2004, Capital social: 20.000.000 lei